

MOTORTRONICS

SSRV STARTERS

IN STOCK INVENTORY UP TO 300 H.P.

VMX-H SERIES HEAVY DUTY CONFIGURED SOFT STARTER WITH CIRCUIT BREAKER

FEATURES:

- NEMA 12 Enclosure
- Circuit breaker w/ Door Operator
- VMX Heavy Duty Digital Starter
- Built-In-Line Start Rated Bypass
- 110V Control Power Transformer
- Soft Start or Across-the-line Switch
- Terminal Strip for Customer Interface
- Heavy Duty Rated (500% for 30 seconds)

FEATURES OF THE SMART DOOR:

- Keypad
 - Programming, Diagnostics, Metering
- Emergency Stop Pushbutton
- Start/Stop Pushbutton
- Local/Off/Remote Switch
- Motor Run Light
- Start Fault Light
- External Interlock Light




**** Flip over for VMX-H Dimension Details***

Configured VMX Series- Heavy Duty Soft Starter with Circuit Breaker

Model Number	Max Amp Rating	Nominal Motor HP Rating				Circuit Breaker Ratings (AMPS)	Frame Size
		220v	230v	460v	575v		
VMX-H-21CB	21	5	5	15	10-15	30	1
VMX-H-27-CB	27	7.5	7.5	20	20	60	1
VMX-H-40-CB	40	10	10	25	25	60	1
VMX-H-45-CB	45	10	15	30	30	60	1
VMX-H-55-CB	55	15	20	40	40	100	1
VMX-H-68-CB	68	20	25	50	50	150	1
VMX-H-80-CB	80	25	30	50	50	150	1
VMX-H-96-CB	96	30	30	60	60	150	1
VMX-H-125-CB	125	40	40	75	75	225	1
VMX-H-156-CB	156	50	50-60	100-125	100-125	225	2
VMX-H-220-CB	220	60	75	150	150	400	2
VMX-H-248-CB	248	75	100	200	200	400	2
VMX-H-312-CB	312	100	125	250	250	400	2
VMX-H-400-CB	400	125	150	300	300	600	2
VMX-H-480-CB	480	150	200	400	350-500	600	2
VMX-H-600-CB	600	200	250	500	600	800	2
VMX-H-690-CB	690	250	250	500	600	1200	3
VMX-H-800-CB	800	250	300	600	600	1200	3
VMX-H-960-CB	960	300	300-400	700-800	700-900	1200	3
VMX-H-1080-CB	1080	350	450	900	1000	C/F	3

VMX-H DIMENSIONS:

FRAME SIZE	NEMA 4/12	NEMA 12	DIMENSIONS
1	Wall Mount	Wall Mount	37 x 15 x 12
2	Wall Mount	Wall Mount	48 x 33 x 16
3	N/A	Floor Standing	92 x 36 x 30



FOR MORE INFORMATION CALL YOUR LOCAL KJ ELECTRIC REPRESENTATIVE TODAY!

CORPORATE HEADQUARTERS:

admin@kjelectric.com

SYRACUSE: 5894 East Molloy Road, Syracuse NY 13211
(315) 454-5535 • FAX: (315) 455-5564 • www.kjelectric.com



ALBANY

albany@kjelectric.com
146 Railroad Ave
Albany, NY 12205
(518) 783-7152
FAX: (518) 783-7378

BINGHAMTON

binghamton@kjelectric.com
119 Corporate Drive
Binghamton, NY 13904
(607) 772-1760
FAX: (607) 772-1127

BUFFALO

buffalo@kjelectric.com
170 Fire Tower Drive
Buffalo, NY 14150
(716) 693-2500
FAX: (716) 693-2544

ROCHESTER

rochester@kjelectric.com
54 Pixley Industrial Pkwy, Ext.
Rochester, NY 14624
(585) 426-3900
FAX: (585) 426-0739